



50 Ohm BNC Medium Power Noise Source With A Noise Output ENR Of 15 dB From 10 MHz to 6 GHz

Noise Generators Technical Data Sheet

PE85N1021

Features

- 10 MHz to 6 GHz Frequency Range
- Output Noise ENR 15 dB min
- Flatness 2.0 dB typ
- 28 VDC Operation
- Small Size 1.25" by 0.75" by 0.50"

Applications

- Measure Noise Figure
- Signal Strength Calibrators
- Radar
- Jamming
- SATCOM for BER and NF
- Source of Jitter

Description

The PE85N1021 is a coaxial Noise Source with 15 dB min of Output Noise ENR. The Unit features flatness better than +/- 1.5 dB over the frequency range 10 MHz to 6 GHz. The unit has an BNC Female DC Input Connector and an SMA Female RF Output Connector. Standard operation is from +28 Vdc with a 20 mA maximum current draw. The Noise Source ideal for noise figure measurements and built in test applications. The unit features a small profile housing of 1.25" by 0.75" by 0.50" excluding connectors, ideal when space is at a premium.

Electrical Specifications

RF Characteristics

Description	Minimum	Typical	Maximum	Units
Frequency Range	0.01		6	GHz
Impedance		50		Ohms
Output ENR	15			dB
Flatness		±1.5		dB
VSWR			1.35:1	
Output Variation vs Input Voltage			0.1	dB/%V
Output Variation vs Temperature			0.01	dB/deg C
Bias Voltage 1		28		Volts
Input Current 1			25	mA
Calibration Points		1 GHz Step		

Mechanical Specifications

Size

Length	1.25 in [31.75 mm]
Width/Dia.	0.75 in [19.05 mm]
Height	0.5 in [12.7 mm]

Package Type	Connectorized Module
--------------	----------------------

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [50 Ohm BNC Medium Power Noise Source With A Noise Output ENR Of 15 dB From 10 MHz to 6 GHz PE85N1021](#)



50 Ohm BNC Medium Power Noise Source With A Noise
Output ENR Of 15 dB From 10 MHz to 6 GHz

Noise Generators Technical Data Sheet

PE85N1021

Connectors

DC Connector
Output Connector

BNC Female
SMA Male

Environmental Specifications

Temperature

Operating Range
ESD Sensitivity

-20 to 75 deg C
ESD Sensitive Material, Transport material in Approved
ESD bags. Handle only in ESD Workstation.



Compliance Certifications (visit www.Pasternack.com for current document)

Not RoHS Compliant
REACH Compliant

01/01/1753

Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [50 Ohm BNC Medium Power Noise Source With A Noise Output ENR Of 15 dB From 10 MHz to 6 GHz PE85N1021](#)




50 Ohm BNC Medium Power Noise Source With A Noise Output ENR Of 15 dB From 10 MHz to 6 GHz

Noise Generators Technical Data Sheet

PE85N1021

Typical Performance Data





Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [50 Ohm BNC Medium Power Noise Source With A Noise Output ENR Of 15 dB From 10 MHz to 6 GHz PE85N1021](#)



50 Ohm BNC Medium Power Noise Source With A Noise Output ENR Of 15 dB From 10 MHz to 6 GHz

Noise Generators Technical Data Sheet

PE85N1021




50 Ohm BNC Medium Power Noise Source With A Noise Output ENR Of 15 dB From 10 MHz to 6 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [50 Ohm BNC Medium Power Noise Source With A Noise Output ENR Of 15 dB From 10 MHz to 6 GHz PE85N1021](#)

PE85N1021 CAD Drawing

50 Ohm BNC Medium Power Noise Source With A Noise

Output ENR Of 15 dB From 10 MHz to 6 GHz



NOTES:
 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
 3. DIMENSIONS ARE IN INCHES [mm].

DWG TITLE
PE85N1021

PE PASTERNAK
 THE ENGINEER'S RF SOURCE
 Pasternack Enterprises, Inc.
 P.O. Box 16759 | Irvine | CA | 92623
 Phone: (949) 261-1920 | Fax: (949) 261-7451
 Website: www.pasternack.com | E-Mail: sales@pasternack.com

FSCM NO. 53919

CAD FILE 110515

SCALE N/A

SIZE A

2233