



SPECIFICATIONS

FREQUENCY RANGE: 26.5-40 GHz
 OPTIMIZED FROM 0° TO 360°
 MINIMUM PHASE RANGE: 0° TO 500°
 TYPICAL 0 DEGREE GROUP DELAY: 670
 PICOSECONDS
 INSERTION LOSS: 2.5 db MAX
 VSWR: 2.0:1 MAX
 RF POWER: 20 WATTS AVERAGE



PASTERNAK ENTERPRISES, INC.

P.O BOX 16759, IRVINE, CA 92623
 PHONE (949) 261-1920 FAX (949) 261-7451

WEB ADDRESS: www.pasternack.com
 E-MAIL ADDRESS: sales@pasternack.com

COAXIAL & FIBER OPTICS

DWG TITLE
PE8249

DES. 2.92mm PHASE SHIFTER
 FREQUENCY RANGE: 26.5 - 40 GHz

| | | | | | |
|--------|----------------|-----------------|-----------|--------|------|
| REV. B | FSCM NO. 53919 | CAD FILE 110711 | SCALE N/A | SIZE A | 2233 |
|--------|----------------|-----------------|-----------|--------|------|

NOTES:
 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
 3. DIMENSIONS ARE IN INCHES [mm].