



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)577-9887
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5020RE-002

500 - 1000 MHz
200 WATTS

Solid State Broadband High Power RF Amplifier

The 5020RE-002 is a 200 Watt broadband amplifier that covers the 500 – 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5020RE-002 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	500 – 1000 MHz
2	Saturated Output Power	200 Watts typ
3	Power Output @ 1dB Comp.	150 Watts min
4	Small Signal Gain	+53 dB min
5	Small Signal Gain Flatness	± 1.5 dB max
6	Third Order Intercept Point	+60 dBm
7	Input/Output VSWR	2:1 typ (@ 50 Ohms)
8	Harmonics	-20 dBc typical @ 150 Watts
9	Spurious Signals	-60 dBc typical @ 150 Watts
10	Input/Output Impedance	50 Ohms nominal
11	Power Consumption	900 Watts
12	AC Input	100 – 240 VAC, single phase
13	RF Input Overdrive	+10 dB over 1 dB Comp. Point
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB Linear
Mechanical		
16	Dimensions	19" x 5.25" x 20"
17	Weight	48 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

INCLUDED FEATURES

- ◇ RS-232 Communications Interface
- ◇ Rear Panel Connectors
- ◇ ALC + Gain Adjust
- ◇ LCD Digital Display
- ◇ Rack Mountable

OPHIR_{RF} INC. PROPRIETARY AND CONFIDENTIAL INFORMATION

