

SPECIFICATION SHEET

JFW MODEL 50P-2038

SOLID STATE PROGRAMMABLE ATTENUATOR

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	200-6000 MHz
Impedance	50 Ohms nominal
Attenuation Range	0-31 dB in 1 dB steps
Attenuation Steps	1, 2, 4, 8 and 16 dB
VSWR	1.8:1 maximum 200-800 MHz 1.5:1 maximum 800-6000 MHz
Attenuation Accuracy (guaranteed monotonic)	± 0.50 dB 1-7 dB ± 1.00 dB 8-11 dB ± 1.25 dB 12-32 dB (whichever is greater)
Insertion Loss	3.2 dB maximum 1.4 dB typical @ 200 MHz 1.5 dB typical @ 800 MHz 2.0 dB typical @ 2000 MHz 3.0 dB typical @ 6000 MHz
RF Input Power	+20 dBm (operating) +25 dBm (no damage)
Switching Speed	1 microsecond maximum 0.7 microseconds typical
DC Supply	+5Vdc @ 50mA nominal
Control	USB control
Test Software (Microsoft .NET 4.0+) (Windows Vista or greater)	The included JFW software allows control of multiple USB devices. JFW managed library available for development in user made applications.
DC Connector	USB MINI-B 6' USB A to USB Mini-B Cable Included
RF Connector	SMA
Operating Temperature Range	-40°C to +85°C
Physical Size	See outline drawing 092-8061

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	01/18/2016		CLK 01/18/2016				
26297	02/12/2016	A	CLK 02/12/2016				