

# KR Electronics

## General Description


KR 2820-6.7 is a 6.7 MHz bandpass filter. The filter has a minimum 3 dB bandwidth of 2.5 MHz and is designed for a source and load impedance of 50 Ω. Other passband frequencies are available. Please consult the factory.

## Features


- 6.7 MHz Center Frequency
- 50 Ω Source and Load

## Typical Performance

**Passband Amplitude & Group Delay**  
(1 dB/div and 100 nsec/div)



**Overall Response**  
(10 dB/div)



KR Electronics, Inc.  
91 Avenel Street  
Avenel, NJ 07001

Web www.krfilters.com  
Email sales@krfilters.com  
Phone (732) 636-1900  
Fax (732) 636-1982

# KR Electronics 2820-6.7

## Specifications

Parameter	Specification
Filter type	Bandpass
Center Frequency	6.7 MHz
Insertion Loss	< 2.5 dB ( 1.5 dB typical)
Attenuation at 5.45 MHz	3 ± 1 dB
Attenuation at 7.95 MHz	3 ± 1 dB
Attenuation at 2.95 MHz	> 60 dB
Attenuation at 10.45 MHz	> 60 dB
Source and Load	50 Ω

## Physical Dimensions



Dimensions in inches  
Epoxy Case

