



50 Ohm 2 Way SMA Power Divider From 4 GHz to 8 GHz Rated at 10 Watts

TECHNICAL DATA SHEET

PE2080

50 Ohm 2 Way SMA Power Divider From 4 GHz to 8 GHz Rated at 10 Watts

Configuration

Input Connector SMA Male
Output Connectors SMA Female
Frequency Range, GHz 4 to 8
Design Reactive
Number of Output Ports 2

Electrical Specifications

Frequency Range, GHz 4 to 8
Impedance, Ohms 50
Maximum Insertion Loss, dB 0.4
Maximum Input Power, Watts 10
Maximum Input VSWR 1.3:1
Minimum Isolation, dB 20

Mechanical Specifications

Size

 Length, in [mm]
 1 [25.4]

 Width, in [mm]
 1.75 [44.45]

 Height, in [mm]
 0.5 [12.7]

Compliance Certifications (visit www.Pasternack.com for current document)

Plotted and Other Data

Notes: Values at 25 °C, sea level

50 Ohm 2 Way SMA Power Divider From 4 GHz to 8 GHz Rated at 10 Watts from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 50 Ohm 2 Way SMA Power Divider From 4 GHz to 8 GHz Rated at 10 Watts PE2080

URL: http://www.pasternack.com/2-way-sma-power-divider-4-8-ghz-10-watts-pe2080-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.



PE2080 CAD Drawing50 Ohm 2 Way SMA Power Divider From 4 GHz to 8 GHz Rated at 10 Watts

