

SPECIFICATION SHEET
JFW MODEL 50PM-123-XX
PANEL MOUNTED ROTOR

JFW Industries, Inc.
 Phone: 317-887-1340
 sales@jfwindustries.com
 www.jfwindustries.com

Configuration Panel mounted 50DR-143 rotary attenuator(s) on a 19 inch rack mountable panel

Attenuation Range 0-80 dB in 1 dB steps

Frequency Range DC-3000 MHz

Impedance 50 Ohms nominal

VSWR 1.7:1 maximum
1.5:1 typical

Insertion Loss 1.3 dB maximum
0.8 dB typical @ 3000 MHz

Attenuation Accuracy ± 0.5 dB (1 dB steps)
± 0.7 dB or 4% (10 dB steps)

RF Input Power 2 Watts average
1000 Watts peak

Direction of Rotation Attenuation increases in a Clockwise direction

Indexing 30 degrees with stops at minimum and maximum

RF Connector N female or SMA female

Operating Temperature Range -20°C to +85°C

Outline Drawing Numbers 092-8564 (1RU models)
092-8565 (2RU models)

Available 1RU Models (add RF connector type to complete model number)

50PM-123-01	(1 attenuator)
50PM-123-02	(2 attenuators)
50PM-123-03	(3 attenuators)
50PM-123-04	(4 attenuators)
50PM-123-01-3EP	(1 attenuator, 3 extra positions)
50PM-123-02-2EP	(2 attenuators, 2 extra positions)
50PM-123-03-1EP	(3 attenuators, 1 extra positions)

Available 2RU Models (add RF connector type to complete model number)

50PM-123-06	(6 attenuators)
50PM-123-08	(8 attenuators)
50PM-123-01-7EP	(1 attenuator, 7 extra positions)
50PM-123-02-6EP	(2 attenuators, 6 extra positions)
50PM-123-03-5EP	(3 attenuators, 5 extra positions)
50PM-123-04-4EP	(4 attenuators, 4 extra positions)
50PM-123-05-3EP	(5 attenuators, 3 extra positions)
50PM-123-06-2EP	(6 attenuators, 2 extra positions)
50PM-123-07-1EP	(7 attenuators, 1 extra position)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	06/06/2016		TRS 06/06/2016				