



WR-90 to N Female Waveguide to Coax
Adapter 8.2 GHz to 12.4 GHz

TECHNICAL DATA SHEET

PE9801

WR-90 to N Female Waveguide to Coax Adapter 8.2 GHz to 12.4 GHz

Configuration

Waveguide Interface	WR-90
RF Connector	N Female
RF Connector Impedance	50 Ohms

Electrical Specifications

Frequency Range, GHz	8.2 to 12.4
Maximum VSWR	1.3:1

Mechanical Specifications

Size

Length, in [mm]	2.3 [58.42]
Width/Dia., in [mm]	1.63 [41.4]
Height, in [mm]	1 [25.4]
Weight, lbs [g]	0.158 [71.67]

Waveguide Interface

Type	WR-90
Body Material and Plating	Aluminum

RF Connector

Type	N Female
Body Material and Plating	Passivated Stainless Steel

Compliance Certifications (visit www.Pasternack.com for current document)

Plotted and Other Data

Notes: Values at 25 °C, sea level

WR-90 to N Female Waveguide to Coax Adapter 8.2 GHz to 12.4 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [WR-90 to N Female Waveguide to Coax Adapter 8.2 GHz to 12.4 GHz PE9801](http://www.pasternack.com/wr-90-n-female-waveguide-coax-adapter-8.2-ghz-12.4-ghz-pe9801-p.aspx)

URL: <http://www.pasternack.com/wr-90-n-female-waveguide-coax-adapter-8.2-ghz-12.4-ghz-pe9801-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.




PE9801 CAD Drawing

WR-90 to N Female Waveguide to Coax Adapter 8.2 GHz to 12.4 GHz

WR90		Inches	mm
A		1.220	31.0
H		1.630	41.4
J		1.280	32.5
K		0.900	22.9
L		0.400	10.2

M	0.230	5.8
N	1.000	25.4
O (TYP.)	1.860	47.2
Q	0.669	17.0
T (TYP.)	2.300	58.4



BACK VIEW

DWG TITLE

PE9801

NOTES:
 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
 3. DIMENSIONS ARE IN INCHES [mm].

FSCM NO. 53919

231

SIZE A

SCALE N/A

CAD FILE 013113-A

PE PASTERNAK®
 Pasternack Enterprises, Inc.
 P.O. Box 16759 | Irvine | CA | 92623
 Phone: (949) 261-1920 | Fax: (949) 261-7451
 Website: www.pasternack.com | E-Mail: sales@pasternack.com