

SPECIFICATION SHEET
JFW MODEL 50PM-125-XX
PANEL MOUNTED ROTOR

JFW Industries, Inc.
 Phone: 317-887-1340
 sales@jfwindustries.com
 www.jfwindustries.com

Configuration Panel mounted 50DR-082 rotary attenuator(s) on a 19 inch rack mountable panel

Attenuation Range 0-110 dB in 1 dB steps

Frequency Range DC-2000 MHz

Impedance 50 Ohms nominal

VSWR 1.2:1 maximum DC-500 MHz
 1.4:1 maximum 500-1000 MHz
 1.5:1 maximum 1000-2000 MHz

Insertion Loss 0.5 dB maximum DC-1000 MHz
 1.0 dB maximum 1000-2000 MHz

Attenuation Accuracy ± 0.5 dB or 2% DC-500 MHz
 ± 0.5 dB or 3% 500-2000 MHz
 (whichever is greater)

RF Input Power 2 Watts average
 1000 Watts peak

Direction of Rotation Attenuation increases in a Clockwise direction

Indexing 30 degrees with stops at minimum and maximum

RF Connector BNC, N, SMA or TNC female

Operating Temperature Range -20°C to +85°C

Outline Drawing Numbers 092-8564 (1RU models)
 092-8565 (2RU models)

Available 1RU Models 50PM-125-01 (1 attenuator)
 (add RF connector type to 50PM-125-02 (2 attenuators)
 complete model number) 50PM-125-03 (3 attenuators)
 50PM-125-04 (4 attenuators)
 50PM-125-01-3EP (1 attenuator, 3 extra positions)
 50PM-125-02-2EP (2 attenuators, 2 extra positions)
 50PM-125-03-1EP (3 attenuators, 1 extra positions)

Available 2RU Models 50PM-125-06 (6 attenuators)
 (add RF connector type to 50PM-125-08 (8 attenuators)
 complete model number) 50PM-125-01-7EP (1 attenuator, 7 extra positions)
 50PM-125-02-6EP (2 attenuators, 6 extra positions)
 50PM-125-03-5EP (3 attenuators, 5 extra positions)
 50PM-125-04-4EP (4 attenuators, 4 extra positions)
 50PM-125-05-3EP (5 attenuators, 3 extra positions)
 50PM-125-06-2EP (6 attenuators, 2 extra positions)
 50PM-125-07-1EP (7 attenuators, 1 extra position)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	06/06/2016		TRS 06/06/2016				