Surface Mount

Voltage Controlled Oscillator

ROS-3555+

Linear Tuning 3000 to 3555 MHz

Features

- linear tuning characteristics
- low phase noise
- low pushing & pulling
- aqueous washable

Applications

- defense systems
- wireless communications
- SAP/ SAB
- satellite systems
- radar

CASE STYLE: CK605
PRICE: $15.95 ea. QTY (5-49)

+RoHS Compliant
The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

Electrical Specifications

MODEL NO.	FREQ. (MHz)		POWER OUTPUT (dBm)	PHASE NOISE dBc/Hz SSB at offset frequencies,kHz				TUNING					NON HARMONIC SPURIOUS (dBc)	HARMONICS (dBc)		PULLING pk-pk @12 dBr (MHz)	PUSHING (MHz/V)	DC OPERATING POWER	
				Typ.				VOLTAGE RANGE (V)		SENSI-TIVITY (MHz/V)	PORT CAP (pF)	3 dB MODULATION BANDWIDTH (MHz)						Vcc (volts)	Current (mA)
	Min.	Max.	Typ.	1	10	100	1000	Min.	Max.	Typ.	Typ.	Typ.	Typ.	Typ.	Max.	Typ.	Typ.		Max.
ROS-3555+	3000	3555	+5	-71	-97	-118	-138	0.5	15	60-70	12	55	-90	-25	-15	1.5	3	5	41

Pin Connections

RF OUT	10
VCC	14
V-TUNE	2
GROUND	1,3,4,5,6,7,8,9,11,12,13,15,16

Maximum Ratings

Operating Temperature	-55°C to 85°C
Storage Temperature	-55°C to 100°C
Absolute Max. Supply Voltage (Vcc)	7V
Absolute Max. Tuning Voltage (Vtune)	16V
All specifications	50 ohm system

Permanent damage may occur if any of these limits are exceeded.

Outline Drawing



Demo Board MCL P/N: TB-10
Suggested PCB Layout (PL-012)



NOTES:

1. TRACE WIDTH IS SHOWN FOR FR4 WITH DIELECTRIC THICKNESS .030" ± .002"; COPPER: 1/2 OZ. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH MAY NEED TO BE MODIFIED.
2. BOTTOM SIDE OF THE BOTTOM IS CONTINUOUS GROUND PLANE.

DENOTES PCB COPPER LAYOUT WITH SMOBC (SOLDER MASK OVER BARE COPPER)

DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK

Outline Dimensions (inch / mm)

A	B	C	D	E	F	G	H	J	K	L	M	N	P	Q	R	S	T	wt.
.500	.500	.180	.100	.080	.115	.060	.040	.540	.060	.100	.135	.135	.115	.140	.070	.150	.070	grams
12.70	12.70	4.57	2.54	2.03	2.92	1.52	1.02	13.72	1.52	2.54	3.43	3.43	2.92	3.56	1.78	3.81	1.78	1.0

Performance Data & Curves*

ROS-3555+

V TUNE	TUNE SENS (MHz/V)	FREQUENCY (MHz)			POWER OUTPUT (dBm)			Icc (mA)	HARMONICS (dBc)			FREQ. PUSH (MHz/V)	FREQ. PULL (MHz)	PHASE NOISE (dBc/Hz) at offsets				FREQ OFFSET (KHz)	PHASE NOISE at 3278 MHz (dBc/Hz)
		-55°C	+25°C	+85°C	-55°C	+25°C	+85°C		F2	F3	F4			1kHz	10kHz	100kHz	1MHz		
0.00	113.54	2799.8	2782.5	2764.9	5.50	5.34	4.70	34.22	-26.2	-33.0	-54.0	1.41	2.22	-66.8	-92.8	-113.4	-133.8	1.0	-70.09
0.50	94.59	2854.5	2839.2	2831.6	5.48	5.26	4.58	34.28	-26.0	-34.7	-56.0	2.05	1.07	-68.7	-94.4	-115.6	-135.6	2.0	-78.93
1.00	83.58	2900.2	2886.5	2879.1	5.42	5.28	4.75	34.27	-27.1	-37.2	-56.5	2.05	2.07	-69.9	-95.6	-116.2	-136.0	3.5	-85.37
2.00	69.89	2978.5	2966.1	2958.5	5.48	5.27	4.82	34.31	-26.9	-38.6	-57.7	2.43	1.34	-70.4	-95.4	-116.5	-136.8	6.0	-90.90
3.00	64.51	3047.6	3035.9	3028.0	5.40	5.17	4.73	34.36	-25.9	-37.0	-60.3	2.56	1.36	-70.5	-96.1	-117.1	-137.4	8.5	-94.45
4.00	62.08	3113.0	3101.1	3092.8	5.30	5.07	4.82	34.40	-26.2	-39.7	-58.4	2.56	2.35	-70.4	-96.2	-117.5	-137.4	10.0	-96.04
5.00	61.06	3174.7	3162.8	3154.2	5.21	5.05	4.75	34.49	-25.4	-42.6	-53.8	2.56	2.27	-70.9	-95.7	-117.9	-137.8	20.8	-103.66
6.00	60.42	3236.1	3224.2	3215.2	5.22	4.98	4.74	34.56	-24.7	-39.0	-56.3	2.69	2.06	-72.8	-96.2	-117.8	-137.9	35.5	-108.90
7.00	61.06	3297.3	3285.1	3275.8	5.10	4.98	4.83	34.66	-26.4	-41.3	-59.0	3.07	1.34	-70.9	-96.9	-118.0	-138.3	60.7	-113.50
8.00	61.70	3358.8	3346.6	3336.9	5.13	4.97	4.77	34.82	-26.6	-43.0	-57.3	3.07	0.57	-71.5	-97.0	-118.6	-139.1	86.7	-116.93
9.00	63.74	3422.0	3409.5	3399.5	4.90	4.79	4.77	34.96	-25.0	-43.0	-57.7	3.33	0.43	-70.4	-97.5	-118.5	-138.8	100.0	-118.09
10.00	66.94	3486.9	3474.0	3463.7	4.94	4.93	4.73	35.13	-25.2	-44.8	-59.4	3.33	0.82	-69.5	-96.6	-118.7	-139.1	148.1	-121.59
11.00	68.74	3554.3	3541.3	3530.8	5.02	4.82	4.63	35.36	-24.2	-46.0	-59.4	3.46	0.97	-70.0	-96.2	-119.0	-139.1	177.0	-123.14
12.00	69.63	3624.3	3610.7	3599.9	4.96	4.85	4.73	35.57	-23.8	-45.8	-59.6	2.94	1.08	-69.8	-96.1	-118.9	-138.9	211.6	-124.82
12.50	68.61	3659.1	3645.5	3634.7	5.10	4.93	4.69	35.71	-23.9	-48.4	-59.4	2.30	1.53	-69.7	-95.5	-118.5	-138.7	302.4	-127.91
13.00	67.84	3693.7	3679.8	3669.2	5.02	4.98	4.67	35.80	-23.8	-48.3	-59.5	1.28	0.88	-68.4	-95.9	-117.9	-138.3	361.5	-129.48
13.50	64.77	3727.4	3713.7	3703.3	4.91	4.84	4.67	35.91	-23.7	-48.1	-58.8	0.00	1.23	-66.8	-95.4	-117.8	-137.7	507.5	-132.39
14.00	61.95	3759.8	3746.1	3735.8	5.01	4.81	4.58	36.01	-24.0	-46.1	-59.5	1.28	1.44	-68.7	-94.7	-117.2	-137.4	606.7	-133.97
14.50	59.26	3791.0	3777.1	3767.0	4.92	4.90	4.49	36.06	-23.5	-44.3	-54.6	2.82	1.13	-68.4	-94.2	-116.8	-137.1	851.6	-136.90
15.00	54.78	3820.7	3806.7	3796.7	4.73	4.71	4.48	36.12	-24.0	-45.3	-45.3	4.22	1.71	-67.1	-93.9	-116.0	-136.4	1000.0	-138.13

*at 25°C unless mentioned otherwise

ROS-3555+
Frequency and Tuning Sensitivity



ROS-3555+
Power Output



ROS-3555+
Harmonics Level



ROS-3555+
Frequency Pulling & Pushing (Vcc ± 5%)



ROS-3555+
Phase Noise Vs. Tuning Voltage



ROS-3555+
Phase Noise