#### **OUTPUTS** Level (into $50\Omega$ ) Output Frequency 10 MHz Α +13 ±2 dBm В 1 GHz +13 +2 dBm **STABILITY Aging** 1 x 10<sup>-7</sup> first vear after 30 days operating, typical 5 x 10<sup>-8</sup> second year, typical 2 x 10<sup>-8</sup> per year thereafter, typical Phase Noise L(f), dBc/Hz, typical 10 MHz 1 GHz

-99

-117

-122

-135

-152

-154

# **Temperature Stability**

-140

-160

-165

-172

-174

-175

±5 x 10<sup>-9</sup>, 0 to +50°C (Ref. +25°C)

### **Harmonics**

10 Hz

100 Hz

300 Hz

10 kHz

100 kHz

1 kHz

≤ -25 dBc

### **Sub-Harmonics**

< -60 dBc

#### PLL Reference Products

≤ -60 dBc

# **Spurious**

≤ -80 dBc, excluding power supply line related spurs

#### **Phase Lock Alarm**

TTL

Locked: +3.5 VDC to +5.2 VDC (Hi) Out-of-Lock: +0.8 VDC max (Lo)

# **Phase Lock Voltage Monitor**

Voltage monitor pin supplied

### **MECHANICAL**

#### **Dimensions**

6.51 x 4 x 1"

#### Connectors

RF Outputs: SMA(f)

Power, Monitoring: Feed Thru Terminals

**GND: Ground Turret** 

# **Packaging**

Nickel-plated machined aluminum housing – J2PMX

### Mounting

Threaded inserts on base, #2-56, 11 places

#### POWER REQUIREMENTS

### Warm-Up Power

≤ 19 Watts for 5 minutes

#### **Total Power**

≤ 12 Watts at +25°C

# Supply Voltage

+15 VDC ±5%

#### **ADJUSTMENT**

Mechanical Tuning (Internal 10 MHz)

±1 x 10<sup>-6</sup>

Loop BW (Internal 100 MHz PLL)

Target Bandwidth: ~250 Hz

Type 2 Loop

#### **CRYSTAL**

## Type

100 MHz SC-cut (x10)

### **OTHER**

### Label

Use conventional label with the following information: 501-25497 (Current Rev.)

10M/1GHz MXO-PLMX

+15 VDC

Serial # - Date Code

(Mark connectors with function)

#### **Test Data**

- Output Level
- Phase Noise
- Temperature Stability
- Harmonics, Subs, Products, Spurs
- Power Warm-up and Total

| REV | DATE     | REVISION RECORD | DWN | AUTH |
|-----|----------|-----------------|-----|------|
| -   | 05-17-12 | Initial Release | PAC |      |
|     |          |                 |     |      |
|     |          |                 |     |      |
|     |          |                 |     |      |
|     |          |                 |     |      |

| J2PMX MXO Connections |                                |  |  |  |
|-----------------------|--------------------------------|--|--|--|
| Connector             | Function                       |  |  |  |
| 1 2                   | Supply Voltage<br>Ground, Case |  |  |  |
| 4                     | RF Output B                    |  |  |  |
| 5                     | Phase Lock Voltage             |  |  |  |
| 6                     | Phase Lock Alarm               |  |  |  |
| 8                     | RF Output A                    |  |  |  |



