



WR-75 to N Female Waveguide to Coax Adapter 10 GHz to 15 GHz

TECHNICAL DATA SHEET

PE9817

WR-75 to N Female Waveguide to Coax Adapter 10 GHz to 15 GHz

Configuration

Waveguide Interface WR-75
Flange Design Standard
RF Connector N Female
RF Connector Impedance 50 Ohms

Electrical Specifications

Frequency Range, GHz 10 to 15 Maximum VSWR 1.25:1

Mechanical Specifications

Size

 Length, in [mm]
 1 [25.4]

 Width/Dia., in [mm]
 1.5 [38.1]

 Height, in [mm]
 2.14 [54.36]

Waveguide Interface

Type WR-75
Body Material and Plating Aluminum

RF Connector

Type N Female

Body Material and Plating Passivated Stainless Steel

Compliance Certifications (visit www.Pasternack.com for current document)

Plotted and Other Data

Notes: Values at 25 °C, sea level

WR-75 to N Female Waveguide to Coax Adapter 10 GHz to 15 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-75 to N Female Waveguide to Coax Adapter 10 GHz to 15 GHz PE9817

URL: http://www.pasternack.com/wr-75-n-female-waveguide-coax-adapter-10-15-ghz-pe9817-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.



PE9817 CAD Drawing

WR-75 to N Female Waveguide to Coax Adapter 10 GHz to 15 GHz

