

SPECIFICATION SHEET
JFW MODEL 50KFA-074 N
FIXED ATTENUATOR KIT

JFW Industries, Inc.
 Phone: 317-887-1340
 sales@jfwindustries.com
 www.jfwindustries.com

Description	Kit of RF components supplied together in a case		
Frequency Range	DC-2200 MHz		
Impedance	50 Ohms nominal		
RF Connectors	N		
RF Input Power	1 Watt average		
Parts Included	(1 piece) 3dB fixed attenuator, N male/female (1 piece) 6dB fixed attenuator, N male/female (1 piece) 10dB fixed attenuator, N male/female (1 piece) 20dB fixed attenuator, N male/female (1 piece) Termination N male		
Model Numbers for Each Individual Part	50F-003 N	(3dB Fixed Attenuator)	
	50F-006 N	(6dB Fixed Attenuator)	
	50F-010 N	(10dB Fixed Attenuator)	
	50F-020 N	(20dB Fixed Attenuator)	
	50T-335 N M	(Termination)	

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	09/24/2014		TRS 09/24/2014				