



[CLICK ON JYEBAO PART NUMBER TO RETRIEVE DATA SHEET](#)

**N 5 Watt Series**

| Part Number     | Figure | Male/<br>Female | Frequency<br>Range (GHz) | Imped.<br>(Ohm) | Power<br>(Watt) | VSWR  |       |       |      |       |
|-----------------|--------|-----------------|--------------------------|-----------------|-----------------|-------|-------|-------|------|-------|
|                 |        |                 |                          |                 |                 | 1G    | 2G    | 3G    | 6G   | 10G   |
| HPT-NM0/3G5W50  | 1      | Male            | 0 to 3GHz                | 50Ω             | 5W              | ≤1.2  | ≤1.25 | ≤1.3  | -    | -     |
| HPT-NM0/6G5W50  | 1      | Male            | 0 to 6GHz                | 50Ω             | 5W              | ≤1.15 | ≤1.2  | ≤1.25 | ≤1.3 | -     |
| HPT-NM0/10G5W50 | 1      | Male            | 0 to 10GHz               | 50Ω             | 5W              | ≤1.05 | ≤1.1  | ≤1.15 | ≤1.2 | ≤1.35 |
| HPT-NF0/3G5W50  | 2      | Female          | 0 to 3GHz                | 50Ω             | 5W              | ≤1.2  | ≤1.25 | ≤1.3  | -    | -     |
| HPT-NF0/6G5W50  | 2      | Female          | 0 to 6GHz                | 50Ω             | 5W              | ≤1.15 | ≤1.2  | ≤1.25 | ≤1.3 | -     |
| HPT-NF0/10G5W50 | 2      | Female          | 0 to 10GHz               | 50Ω             | 5W              | ≤1.05 | ≤1.1  | ≤1.15 | ≤1.2 | ≤1.35 |
| HPT-NM0/1G5W75  | 1      | Male            | 0 to 1 GHz               | 75Ω             | 5W              | ≤1.2  | -     | -     | -    | -     |
| HPT-NM0/2G5W75  | 1      | Male            | 0 to 2 GHz               | 75Ω             | 5W              | ≤1.15 | ≤1.3  | -     | -    | -     |
| HPT-NF0/1G5W75  | 2      | Female          | 0 to 1 GHz               | 75Ω             | 5W              | ≤1.2  | -     | -     | -    | -     |
| HPT-NF0/2G5W75  | 2      | Female          | 0 to 2 GHz               | 75Ω             | 5W              | ≤1.15 | ≤1.3  | -     | -    | -     |