
MODEL 852 - 879 – FF3
IMPEDANCE MATCHING PAD

Frequency Range: DC - 3 GHz

Impedance: 50 Ohms nominal (N Female side)
75 Ohms nominal (F Female side)

Insertion Loss: 5.7 dB nominal

VSWR: 1.40:1 maximum

Input Power: 1 Watt average

Connectors: N Female / F Female

Outline Drawing: MED – 0763

ECF #	Date	Rev.
Issue	3/27/08	0

Approved By: _____