

**SPECIFICATION SHEET**

**JFW MODEL 50DB-009**

**DC BLOCK**

JFW Industries, Inc.  
Phone: 317-887-1340  
sales@jfwindustries.com  
www.jfwindustries.com

Description	Inner Only DC Block
Frequency Range	10-4000 MHz
Impedance	50 Ohms nominal
VSWR	1.3:1 maximum
Insertion Loss	0.3 dB maximum
DC Breakdown Voltage	50 Volts
RF Input Power	2 Watts average
RF Connector	N, BNC, SMA or TNC
Outline Drawing Numbers	092-4159 (N M to N F) 092-429 (BNC M to BNC F) 092-1324 (SMA M to SMA F) 092-4160 (TNC M to TNC F) 092-4942 (BNC F to TNC M)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
2995	05/16/2002	C		11654	08/08/2005	F	SL 08/08/2005
4640	07/15/2004	E	CLV 07/16/2004	11915	09/28/2005	G	BAC 09/28/2005
9999	10/14/2002	D	SL 10/14/2002	26756	06/20/2016	H	TRS 06/20/2016